

ABSTRACT

A thorough study on Bismuth-based Erbium-doped fiber (Bi-EDF) is presented for wide-band amplifiers and multi-wavelength fiber laser applications. This fiber allows high Erbium ions concentration to be doped without a significant concentration quenching effect. The high refractive index characteristic in the Bi-EDF has broadened the emission spectrum of Erbium ions to achieve a broader gain spectrum up to extended L-band region compared to normal silica-based Erbium-doped fiber (EDF). The Bi-EDFA performances have been investigated in terms of power conversion efficiency (PCE), quantum conversion efficiency (QCE), gain and noise figure. The highest QCE and PCE for a 215 cm long of Bi-EDF are estimated to be approximately 23.7% and 25.7%, which is obtained at 1605 nm. With bi-directional pumping, the maximum gain of 34 dB is obtained at approximately 1570 nm. The operation of the bi-directional Bi-EDFA covers from C-band to the extended L-band regions. Furthermore, various configurations on the multi-wavelength fiber lasers have been proposed and demonstrated using the Bi-EDF as both the linear and nonlinear effects. Nonlinear effects such as the stimulated Brillouin scattering (SBS) and four-wave mixing (FWM) are used in the fiber lasers to generate multi-wavelength comb lines. The Brillouin Erbium fiber laser (BEFL) is able to produce a stable comb with 50 lines at extended L-band region using only a Bi-EDF as the gain medium. The multi-wavelength fiber laser has also been demonstrated for the first time based on a Bi-EDF assisted by a FWM process. The estimation of the nonlinear parameters of Bi-EDF was also proposed based on the FWM effect. With a simple ring cavity, the laser generates more than 10 lines of optical comb with a line spacing of approximately 0.41nm at 1615.5 nm region using 146 mW of 1480 nm pump power.

ABSTRAK

Tesis ini melibatkan satu pengajian terperinci tentang gentian terdop-Erbium asas-Bismuth (Bi-EDF) untuk kegunaan laser gentian penguat jalur-lebar dan jarakgelombang pelbagai. Gentian ini membenarkan kepekatan ion yang tinggi untuk didopkan tanpa kesan pelindapkejutan kepekatan signifikan. Ciri indeks biasan dalam Bi-EDF telah membesarkan spektrum pancaran ion erbium untuk mencapai gandaan lebih luas sehingga ke kawasan jalur-L tambahan jika dibandingkan dengan gentian terdop-Erbium (EDF) asas-silika. Perlakuan Bi-EDFA telah diselidiki dalam sebutan efisiensi pertukaran kuasa (PCE), efisiensi pertukaran kuantum (QCE), gandaan dan angka hingar. Nilai QCE dan PCE tertinggi untuk Bi-EDF 215 cm panjang adalah masing-masing 23.7% dan 25.7% pada 1605 nm. Dengan menggunakan pam dwi-arah, gandaan maksimum sebanyak 34dB terdapat disekitaran 1570 nm. Operasi Bi-EDFA dwi-arah meliputi jalur-C sehingga kawasan jalur-L tambahan. Beberapa konfigurasi laser gentian jarakgelombang pelbagai telah dianjurkan dan dipersembahkan dengan menggunakan Bi-EDF sebagai kesan lurus dan tak-lurus. Kesan tak-lurus seperti penyerakan rangsangan Brillouin (SBS) dan campuran empat-gelombang (FWM) telah digunakan didalam gentian laser untuk menghasilkan garis sisir jarakgelombang-pelbagai. Laser gentian Brillouin Erbium (BEFL) dapat menjanakan sisir yang stabil dengan 50 garis pada kawasan jalur-L tambahan dengan hanya menggunakan Bi-EDF sebagai bahantara gandaan. Laser gentian jarakgelombang-pelbagai telah ditunjukkan bagi kali pertama keatas Bi-EDF dibantu oleh proses FWM. Anggaran bagi parameter-parameter tak-lurus Bi-EDF adalah berasaskan pada kesan empat-gelombang campuran (FWM). Dengan menggunakan satu rongga gelang mudah, laser tersebut dapat menjanakan lebih dari 10 garis sisir optik dengan jarak garisan beranggaran 0.41 nm pada kawasan 1615.5 nm dengan menggunakan kuasa pam 146 mW pada 1480 nm.

ACKNOWLEDGMENTS

PhD was the most significant research experience in my life. Hence, it is my pleasure on finishing this PhD thesis, that I consider many peoples who made this work possible. I would like to sincerely express my deepest appreciation to my supervisors, Prof. Dr. Harith Ahmad and Assoc. Prof. Dr. Sulaiman Wadi Harun for their kind advice, support and patience. I also wish to thank to my dear Malaysian and Iranian colleagues in the photonics research center for providing a friendly and warm environment. Their help and generous sharing of knowledge during my research work is greatly appreciated.

My greatest gratitude to my beloved husband, for his never ending support and motivation. In addition, I would like to express my deepest appreciation to my dear son for his love, tolerance and understanding during my study. Last but not least, a special thank you to my wonderful parents for their unconditional love from far way, and for their inspiration and faith in me to complete my study.

LIST OF CONTENTS

	Page
ABSTRACT	i
ABSTRAK	ii
ACKNOWLEDGMENTS	iii
LIST OF CONTENTS	iv
LIST OF FIGURES.....	viii
LIST OF TABLES	xv
LIST OF ABBREVIATIONS	xv

CHAPTER 1

INTRODUCTION

1.1 Optics Communication and Fiber Laser	1
1.2 Overview on Multi-wavelength Fiber Lasers	3
1.3 Nonlinear Effects in Optical Fibers.....	6
1.4 Optical Fiber Amplifiers	8
1.5 Research Objectives	9
1.6 Thesis Overview and Methodology of Research	10
REFERENCES.....	13

CHAPTER 2

LITERATURE REVIEWS ON NONLINEAR EFFECTS, AMPLIFICATION AND FIBER LASERS

2.1 Introduction	18
------------------------	----

2.2	Nonlinear Effects in Optical Fibers.....	20
2.2.1	Inelastic Scattering Effects in Optical Fibers.....	21
2.2.2	Nonlinear Refractive Index Effects or Kerr Effects.....	31
2.3	Applications of the Nonlinear Effects.....	38
2.4	Bismuth-based EDF for Optical Amplification and Nonlinear Devices.....	43
2.4.1	Optical Fiber Amplifiers	44
2.4.2	Background on the Bi-EDF.....	46
2.4.3	Review on Previous Works Using a Bismuth Oxide Fiber.....	52
2.5	Background on the Fiber Lasers	53
2.6	Comparison of the SBS Effects in Various Types of Fibers.....	57
	REFERENCES	62

CHAPTER 3

CHARACTERIZATION OF BISMUTH-BASED ERBIUM DOPED FIBER AMPLIFIERS AND RAMAN AMPLIFICATION

3.1	Introduction.....	78
3.2	Absorption and Emission Characteristics of the Bi-EDF	80
3.3	Amplification Principle and Numerical Model of Bi-EDFA.....	82
3.4	Gain and Noise Figure Performance of the Bi-EDFA	86
3.5	Gain Spectrum.....	90
3.6	Characterization of C-band Bi-EDFA.....	93
3.7	Characterization of L-band Bi-EDFA.....	102
3.8	Double-pass Bi-EDFA	110
3.9	Bi-EDFA with a Bidirectional Pumping.....	113
3.10	Raman Amplification.....	117
	REFERENCES.....	122

CHAPTER 4

SINGLE AND MULTI-WAVELENGTH BISMUTH-BASED BRILLOUIN ERBIUM FIBER LASER

4.1 Introduction.....	126
4.2 Single-wavelength BFL Using Bi-EDF in the Ring Cavity.....	128
4.3 Multi-wavelength BEFL Configuration with a Linear Cavity.....	137
4.4 New Configuration for the BEFL by Changing the Position of the Output Coupler.....	141
4.5 Multi-Wavelength BEFL in a Ring Configuration	146
4.6 Self-excited Multi-wavelength BEFL Using a PCF.....	155
4.7 Incorporation Effect of SMF in a Linear BEFL Cavity Configuration.....	157
4.8 Enhanced Multi-Wavelength BEFL with a Flat Output Spectrum	161
4.9 Multi-Wavelength BEFL with Assistance of Raman Amplification.....	170
REFERENCES.....	175

CHAPTER 5

MULTI-WAVELENGTH BISMUTH ERBIUM DOPED FIBER LASER ASSISTED BY FOUR-WAVE MIXING EFFECT

5.1 Introduction.....	178
5.2 FWM Effects in Open-loop Cavity System Using Various Gain Medium.....	179
5.3 Enhanced FWM Efficiency of Bi-EDF in a New Ring Configuration for Determination of Nonlinear Parameters.....	187
5.4 FWM-based Ring Laser Using 49cm of Bi-EDF for Multi-wavelength Laser Generation	196
5.5 FWM-based Bi-EDF Self-seed Multi-wavelength Laser in the Linear Cavity....	199
5.6 Multi-wavelength Laser Generation with Bi-EDF in Extended L- band Region.	204
5.7 FWM-based Multi-wavelength Laser with Incorporation of PCF in Linear	

Cavity Configuration.....	210
REFERENCES.....	217
 CHAPTER 6	
CONCLUSION AND FUTURE WORKS	
6.1 Conclusion	220
6.2 Future Works.....	227
 APPENDIX A	
LIST OF PUBLICATIONS	228
 APPENDIX B	
SELECTED PAPERS	231

LIST OF FIGURES

CHAPTER 1. INTRODUCTION	Page
1.2 Methodology of research.....	12
 CHAPTER 2. LITERATURE REVIEWS ON NONLINEAR EFFECTS, AMPLIFICATION AND FIBER LASERS	
2.1 Light scattering by an induced dipole moment due to an incident EM wave [15].....	22
2.2 Energy level diagrams describing (a) Raman Stokes scattering and (b) Raman anti-Stokes scattering.....	23
2.3 Spectrum of energy reradiated by stimulated Raman scattering [17].....	25
2.4 Schematic diagram of the SBS process in an optical fiber.....	26
2.5 Spectrum of reflected light from 2.15 m long Bi-EDF with input power of 150 mW and BP wavelength of 1615.8 nm.....	28
2.6 FWM effects in case of partially degenerate (left) and non-degenerate (right) [39].....	37
2.7 Schematic diagram for a standard EDFA.....	45
2.8 Typical Raman nonlinear optical amplifier configuration.....	46
2.9 Illustration on the distribution of Erbium ions in Bismuth-based glass and basic structure of Bismuth oxide [87].....	48
2.10 The cross-section picture of the Bi-EDF, provided by AGC.....	48
2.11 Angled splicing configuration between Bi-EDF and SMF. Silica fiber angle (θ_2) of 8.2° is optimum for Bismuth fiber angle (θ_1) of 6° [89].....	49
2.12 Experimental setup to observe the SBS effect.....	58
2.13 Optical spectrum of the Brillouin scattering effect in PCF, SMF, Bi-EDF and DCF.....	61

CHAPTER 3. CHARACTERIZATION OF BISMUTH-BASED ERBIUM DOPED FIBER AMPLIFIERS AND RAMAN AMPLIFICATION

3.1	Absorption and emission cross-section of Bi-EDF and Si-EDF. (The Bismuth absorption cross-section is obtained from Asahi Glass Co.). The calculated Bismuth emission curve coincides very well with the measured curve [10].	81
3.2	Simplified energy-level diagrams and various transition processes of Er^{3+} ions in silica [15].	83
3.3	Energy level diagram of Er^{3+} and the relevant transitions [16].	83
3.4	Experimental setup for the forward pumped Bi-EDFA.	87
3.5	Variation of gain as a function of Bi-EDF's length for three different input signal wavelengths.	88
3.6	Comparison of calculated gain and noise figure with experimental results for the Bi-EDFA with 49 cm long Bi-EDF.	89
3.7	Theoretical gain versus input signal wavelength and Bi-EDF's length for the Bi-EDFA.	90
3.8	Comparison of the measured signal gain at input signal power of -30 dBm between Si-EDFA and Bi-EDFA. The 1480 nm pump power is fixed at 100 mW.	91
3.9	Comparison of the measured noise figure at input signal power of -30 dBm between Si-EDFA and Bi-EDFA. The 1480 nm pump power is fixed at 100 mW.	92
3.10	Fluorescence spectra of the C-band EDFA configured with 49 cm long Bi-EDF for both forward and backward pumping scheme. The pump power is fixed at 150 mW.	94
3.11	Measured QCE and PCE spectra of the C-band Bi-EDFA at input signal power of 0 dBm.	96
3.12	Forward (a) Gain and (b) Noise figure as a function of input pump power at a fixed signal wavelength of 1535 nm and 1555 nm. The input signal power is fixed at -30 dBm.	98
3.13	Forward gain of one-stage 49cm Bi-EDFA as a function of different wavelengths measured by scan method. The -30 dBm and 0 dBm as input signal levels compared at fixed pump power of 150 mW.	99

3.14	Forward noise figure of one-stage Bi-EDFA as a function of different wavelengths measured by scan method. The -30 dBm and 0 dBm as input signal levels compared at fixed pump power of 150 mW.....	100
3.15	Configuration of the Bi-EDFA with the backward pumping scheme.	100
3.16	Gain and noise figure spectra of the backward pumped C-band Bi-EDFA at input signal powers of -30 dBm and 0 dBm. The 1480 nm pump power is fixed at 150 mW.	101
3.17	The forward and backward ASE spectrum from the Bi-EDFA with 215cm long of gain medium and 160 mW of the 1480 nm pump power.....	103
3.18	Measured QCE and PCE at 0 dBm input signal power from 1525 nm to 1570 nm for 215 cm of Bi-EDF.	104
3.19	Gain and noise figure as a function of input power at a fixed signal wavelength of 1590 nm and 1610 nm.....	105
3.20	Gain and noise figure against 1480 nm pump power at a fixed signal wavelength of 1590 nm and 1610 nm. The input signal power is fixed at -30 dBm.	107
3.21	Gain and noise figure spectra of the forward pumped Bi-EDFA.	108
3.22	Gain and noise figure spectra of the backward pumped Bi-EDFA.	109
3.23	Configuration of the double-pass Bi-EDFA with a broadband FBG.	110
3.24	Gain spectra of the double-pass Bi-EDFA at different input signal powers of -30 dBm and 0 dBm. Pump power is fixed at 150 mW.....	111
3.25	Noise figure spectra of the double-pass Bi-EDFA at different input signal powers of -30 dBm and 0 dBm. Pump power is fixed at 150 mW.....	112
3.26	Experiment setup for the bi-directional pumped Bi-EDFA.....	114
3.27	ASE spectrum of the bidirectional pumped Bi-EDFA.	115
3.28	Gain and noise figure spectra of the bi-directional pumped Bi-EDFA at input signal power of -30dBm. The total 1480 nm pump power is 240 mW.	115
3.29	Gain and noise figure as a function of input signal power for the bi-directionally pumped Bi-EDFA. The signal wavelengths are fixed at 1560 nm and 1590 nm while the pump power for each pump is fixed at 120 mW.	116
3.29	Raman gain profiles for a 1510 nm pump in three different fiber types	

SMF, standard single mode fiber; DSF, dispersion shifted fiber; DCF, dispersion compensating fiber [29].	119
3.31 Schematic diagram for optical Raman gain measurement	120
3.32 The comparison of On–off Raman gain spectra for four types of fiber pieces with input signal power of -3 dBm and pump power of 350 mW.....	121
CHAPTER 4. SINGLE AND MULTI-WAVELENGTH BISMUTH-BASED BRILLOUIN ERBIUM FIBER LASER IN CAVITY	
4.1 Configuration of the proposed BEFL.	129
4.2 Free-running spectrum of three lengths of Bi-EDFA in 90/10 output coupler....	130
4.3 Output spectrum of the 215 cm Bi-EDF laser in different coupler ratio (Without BP).	132
4.4 The output spectrum of the ring BEFL at different output coupler ratios.....	133
4.5 Output spectra of the BFL Bi-EDF based at different power of 1480 nm pump in 20% output.....	134
4.6 The output spectrum of the BEFL at various BP wavelength using 80/20 output coupler.	135
4.7 Output spectra of the BFL based on Bi-EDF at different signal input powers.....	136
4.8 Configuration of the proposed multi-wavelength BEFL with a linear cavity configuration.	138
4.9 Output spectrum of BEFL at different C2 coupling ratios. The laser diode and BP powers are fixed at 155mW and 7dBm, respectively at room temperature.	139
4.10 Multi-wavelength spectra at different combination 1480 nm pump powers. The BP power and wavelength is fixed at 5 dBm and 1615.6 nm, respectively.....	140
4.11 Configuration of the proposed new BEFL with the output coupler placed in the middle of linear cavity.	142
4.12 The output spectra of the proposed BEFL at various 1480 nm pump powers...	144
4.13 The comparison on output spectrum for different lengths of Bi-EDF.	145

4.14	Photonic Crystal Fibers Types, (a) Solid core PCF, (b) Hollow core PCF....	146
4.15	The Scanning Electron Micrograph (SEM) of the PCF cross section and an enlarged view of the central “holey” cladding.	147
4.16	Configuration of multi-wavelength BFL.	148
4.17	Free-running spectrum of the BEFL using 80/20, 90/10 and 95/5 couplers. .	150
4.18	The BFL output spectrum for (a) 80/20 coupler, (b) 90/10 coupler and (c) 95/5 coupler. Both pumps are at the same power for each output coupling ratio.	151
4.19	BFL output spectra with and without PC.	153
4.20	Output peak power as a function of 1480 nm total pump powers. Inset shows the peak power against BP power.	154
4.21	The BFL output spectrum of ring cavity resonator.	155
4.22	The output spectrum of the BEFL using PCF and sagnac loop filter.	156
4.23	The output spectrum of the BEFL using PCF with different pump power.	157
4.24	Configuration of the BEFL with a linear cavity.	158
4.25	The output spectra of three types gain media in port A.	159
4.26	The comparison of output spectra of the BEFL with (a) PCF, (b) SMF at different output ports.	160
4.27	Output power against BP power for the BEFLs configured with and without SMF.	161
4.28	Experimental configuration of the proposed linear cavity BEFL.	163
4.29	Free-running spectrum of the BEFL (without BP). The powers of P1 and P2 are fixed at 120 mW.	164
4.30	Output spectrum of BEFL at different C2 coupling ratios. The P1, P2 And BP powers are fixed at 120 mW, 120 mW and 7 dBm, respectively.	165
4.31	Multi-wavelength spectra at different combination 1480nm pump powers. The BP power and wavelength is fixed at 7dBm and 1569.0 nm, respectively. (a) P1 = P2 =120 mW, (b) P1 = P2 =105 mW, (c) P1 =60 mW, P2 = 100 mW And (d) P1 =105 mW, P2 = 60 mW.	166
4.32	Number of BEFL lines against BP wavelength at different injected BP power. Both the P1 and P2 pump powers are fixed at 120 mW.	168

4.33	BEFL output spectra at BP wavelength of 1568.2nm and BP power of 5 dBm.	169
4.34	Experimental setup for multi-wavelength comb generation based Bi-EDF.....	170
4.35	The multi-wavelength comb generation that includes and excludes Raman pump for the proposed BFL. Inset shows the comb spectrum for the BFL configured without the FBG.....	172
4.36	(a) The number of lines and (b) flat amplitude bandwidth against the injected BP wavelengths at various BP powers.....	174

CHAPTER 5. MULTI-WAVELENGTH BISMUTH ERBIUM DOPED FIBER LASER ASSISTED BY FOUR-WAVE MIXING EFFECT

5.1	Experimental setup for the observation of FWM induced sidebands in different fibers under test.....	180
5.2	A comparison of dual-wavelength output spectrum at 0.5nm spacing of 49 cm and 215 cm Bi-EDF in C- and L- band region, respectively.....	181
5.3	Optical spectra obtained from the different spacing-tunable dual-wavelength source using SMF, PCF and Bismuth.	183
5.4	A comparison of idler output power of three fibers as a function of wavelength spacing.	184
5.5	Ratio of idler power to input signal power as a function of the different spacing wavelength signals.....	185
5.6	Measured optical spectrum in 0.5 nm spacing between two signals.....	186
5.7	The ratio of the idler power to the signal power as a function of wavelength for the system configured with and without the PCF.....	187
5.8	Experimental setup based on CW dual-wavelength method in ring Bi-EDF laser configurations.	189
5.9	Output spectrum of the CW FWM method in ring based only Bi-EDF, spacing between two signals (1612nm and 1613nm) is 1nm.....	190
5.10	Measured ratio of the idler power to the first signal power as a function of wavelength in the two design based Bi-EDF.....	193

5.11	FWM efficiency as a function of fiber length. Inset shows that nonlinear phase shift as a function of input power.....	196
5.12	Proposed configuration of ring cavity based Bi-EDF.....	197
5.13	The output spectrum of the Bi-EDF laser (a) without and (b) with the PCF at 150 mW pump power from 1480 nm laser source.....	198
5.14	Experimental set-up for the proposed a Bi-EDF based multi-wavelength laser.....	199
5.15	Output spectrum of the proposed Bi-EDF based multi-wavelength Laser at different output ports.....	200
5.16	Output spectrum of the proposed Bi-EDF based multi-wavelength laser at 1480 nm of different pump powers.....	202
5.17	Peak powers of 5 middle lines of the output comb against 1480 nm pump power at (a) Port A and (b) Port B.....	203
5.18	Experimental set-up for the proposed a Bi-EDF based multi-wavelength ring laser.....	205
5.19	Output spectrum of the proposed Bi-EDF based multi-wavelength ring Laser at different 1480 nm pump powers.....	207
5.20	The output spectrum when the polarization is un-optimized.....	207
5.21	Peak power against pump power of the 1480 nm laser diode for first 4 lines In the multi-wavelength laser spectrum.....	208
5.22	Multi-wavelength spectra of the ring laser with incorporation of PCF at different 1480nm pump powers.....	209
5.23	Experimental FWM setup for the proposed PCF-based multi-wavelength laser.....	211
5.24	The output spectrum of the multi-wavelength laser at different coupling ratios of C2.....	213
5.25	Multi-wavelength spectra 80/20 coupler at different combination 1480 nm pump powers, P1=P2 (mW) at the same time.....	214
5.26	Schematic of degenerate FWM effect.....	215
5.27	Conservation of multi-wavelength energy in different pump power of BP at 1583.75 nm signal and 80/20 output coupler ratio.....	216

LIST OF TABLES

CHAPTER 2. LITERATURE REVIEWS ON NONLINEAR EFFECTS, AMPLIFICATION AND FIBER LASERS

2.1	The Bi-EDF parameters (at operating wavelength of 1.55 μm).....	51
2.2	Physical fiber parameters	60

LIST OF ABBREVIATIONS

A_{eff}	Effective Area
ASE	Amplified Spontaneous Emission
BEFL	Brillouin Erbium Fiber Laser
BFL	Brillouin Fiber Laser
Bi-EDF	Bismuth-Based Erbium Doped Fiber
Bi-EDFA	Bismuth-Based Erbium Doped Fiber Amplifier
BP	Brillouin Pump
BRFL	Brillouin Raman Fiber Laser(s)
BS	Brillouin Stokes
XPM	Cross-Phase Modulation
CW	Continuous Wave
dB	Decibel
dBm	Decibels above/below one milliwatt
DCF	Dispersion Compensating Fiber
DSF	Dispersion Shifted Fiber
DWDM	Dense Wavelength Division Multiplexing
EDF	Erbium Doped Fiber
EDFA	Erbium Doped Fiber Amplifier
ESA	Excited State Absorption
FP	Fabry-Perot

FBG	Fiber Bragg Grating
FWHM	Full Width at Half Maximum
FWM	Four-Wave Mixing
GVD	Group Velocity Dispersion
HNLF	Highly Nonlinear Fiber
IR	Infra-Red
ITU	International Telecommunications Union
IWDM	Isolator Wavelength Division Multiplexing
LD	Laser Diode
LASER	Light Amplification by the Stimulated Emission of Radiation
LED	Light Emitting diode
L_{eff}	Effective Length
LS	Laser Source
MFD	Mode Field Diameter
MBEFL	Multi-wavelength BEFL
MBFL	Multi-wavelength BFL
MBRFL	Multi-wavelength BRFL
NA	Numerical Aperture
NOA	Nonlinear Optical Amplifier
NOLM	Non-Linear Optical Loop Mirror
OC	Optical Circulator
OPO	Optical Parametric Oscillation
OSA	Optical Spectrum Analyzer
PC	Polarization Controller
PCE	Power Conversion Efficiency
PCF	Photonic Crystal Fiber
PMD	Polarisation Mode Dispersion
PMF	Polarization Maintaining Fiber
P_{th}	Threshold Power
QCE	Quantum Conversion Efficiency
REDFA	Rare-Earth Doped Fibre Amplifier

RF	Radio Frequency
RS	Raman Stokes
RP	Raman Pump
RI	Refractive Index
SBS	Stimulated Brillouin Scattering
SRS	Stimulated Raman Scattering
SMF	Single-Mode Fiber
SMSR	Side-Mode Suppression Ratio
SNR	Signal to Noise Ratio
SOA	Semiconductor Optical Amplifier
SPM	Self-Phase Modulation
TLS	Tunable Laser Source
UV	Ultra-Violet
VOA	Variable optical attenuator
WDM	Wavelength Division Multiplexing
WSC	Wave Selective Coupler
XPM	Cross Phase Modulation
ZDW	Zero-dispersion wavelength